



VELA-AMP

CHARACTERISTICS	EN54 amplifier for PA and voice alarm system. 6 loudspeaker zones, maximum 180 W per zone. Independent volume control per loudspeaker zone. Expandable to 252 zones maximum with VELA-EXT. Message player with 16 MB storage capacity. Error recording and storage. EN 54-16 certified. 6 GPI and 6 GPO. Compatible with DANTE. Software for PC.
POWER	360 W RMS all zones 1 - 6. Maximum 180 W RMS per zone.
RESPONSE	100-15,000 Hz
INPUTS	2 RD ports, for mod. VELA-FMIC, VELA-MIC or VELA-V 3 balanced mics/lines, selectable, XLR, 600 Ohm 20 mV RMS 2 BGM lines, 2 x RCA 10,000 Ohm 300 mV RMS 1 x 100 V line for backup amplifier, euroblock 2 DANTE ports, 2 x RJ-45 (Primary and Secondary) 6 GPI, euroblock 6 emergency control inputs for contact closure fire alarm system, 2 x RJ-45 1 PS LINK for emergency power supply
OUTPUTS	1 REC out, 2 x RCA 6 zone audio outputs for expansion, euroblock 1 LINK for VELA-BUP reserve amplifier, RJ-45 6 GPO, euroblock 2 contact closure status outputs for system flooding, 2 x RJ-45 6 control outputs for dimmers, 24 V DC euroblock
POWER SUPPLY	230 V CA, 1100 W and 24 V CC, 22 A
DIMENSIONS	440 x 130 x 402 mm depth. 2 U 19" rack

WEIGHT

17 kg